

SNR-SFP-ONU-XPON (FW ver. V1.9.0-200831)



ONU ONU SFP-, , SFP- access VLAN.

, SFP-, ONU. OLT.

ONU 192.168.1.1 , = admin / stdONU101

PON:

1. GPON

ONU Stick Module	ONU Stick Module			
		System Status	Advanced Config	System Management User Managenment

[GPON Config](#)

[LAN Config](#)

[VLAN](#)

GPON Settings

This page is used to configure the parameters for your GPON network access.

LOID:

LOID Password:

PLOAM Password:

Serial Number:

OMCI OLT Mode:

Default Mode ▾
Default Mode
Huawei OLT Mode
ZTE OLT Mode
Customized Mode

Apply Changes

ONU Stick Module

ONU Stick Module

[System Status](#) | [Advanced Config](#) | [System Management](#) | [User Management](#)

GPON Config

LAN Config

VLAN

VLAN Settings

☒ Auto

Refresh

☐ Manual

☒ Transparent Mode

☐ Tagging Mode: [0~4095]

Apply Changes

2. EPON

ONU Stick Module

ONU Stick Module

[System Status](#) | [Advanced Config](#) | [System Management](#) | [User Management](#)

EPON Config

LAN Config

VLAN

EPON Settings

This page is used to configure the parameters for your EPON network access.

LOID:

LOID Password:

Apply Changes

LLID MAC mapping Table:

index	LLID	Status	MAC
0	0x7fff	0	<input type="text" value="e0:e8:e6:77:41:fd"/>
1	0x7fff	0	<input type="text" value="00:00:00:00:00:00"/>
2	0x7fff	0	<input type="text" value="00:00:00:00:00:00"/>
3	0x7fff	0	<input type="text" value="00:00:00:00:00:00"/>
4	0x7fff	0	<input type="text" value="00:00:00:00:00:00"/>
5	0x7fff	0	<input type="text" value="00:00:00:00:00:00"/>
6	0x7fff	0	<input type="text" value="00:00:00:00:00:00"/>
7	0x7fff	0	<input type="text" value="00:00:00:00:00:00"/>

Apply Changes

ONU Stick Module

ONU Stick Module

System Status

Advanced Config

System Management

User Management

EPON Config

LAN Config

VLAN

VLAN Settings

Auto

Refresh

Manual

Transparent Mode

Tagging Mode:

[0~4095]

Apply Changes

telnet, ONU, OLT:

GPON/EPON

telnet 192.168.1.1
flash get PON_MODE (View current mode) 1:GPON 2:EPON
flash set PON_MODE 2
reboot

PLOAM

telnet 192.168.1.1
flash set GPON_SN *****
flash set GPON_PLOAM_PASSWD *****

! telnet, "".

<http://192.168.1.1/upgrade.asp>.

! SDK, SDK, ONU, .