

Autoprovision SNR-VP-5x

- 1. Autoprovision
- 2.
- 3. TR069
- 4.
- 5.
- 6. BroadSoft
- 7.
- 8. LDAP
- 9. AreaCode
- 10. Feature ()
- 11. Setting ()
- 12. CallLog
- 13. (Programmable Key)
- 14. Voice
- 15. Tone
- 16. XML Browser
- 17.

1. Autoprovision	
Config.Autoprovision.General.Url	URL- auto provisioning
Config.Autoprovision.General.Username	1 63
Config.Autoprovision.General.Pwd	
Config.Autoprovision.GENERAL.Priority	
Config.Autoprovision.Mode.Mode	auto provision: 0: ; 1: (); 2: ; 3: + .
Config.Autoprovision.Schedule.DayOfWeek	auto provision.
Config.Autoprovision.Schedule.HourOfDay	: 1-7 (-) : 0-23
Config.Autoprovision.AES.Key16	AES (16) .
Config.Autoprovision.AES.Key16Mac	AES (16) MAC
Config.Autoprovision.PNP.Enable	PnP: 0: 1: (-)
Config.Autoprovision.PNP.Url	URL- PnP 1 127
Config.Autoprovision.MD5.GenConfMd5	MD5
Config.Autoprovision.MD5.UrlConfMd5	MD5 MAC
Config.Autoprovision.DHCP_OPTION.Enable	DHCP: 0: 1:
Config.Autoprovision.DHCP_OPTION.CustomId	DHCP: 128 254

Config.Autoprovision.DHCP_OPTION.CustomValue	DHCP CustomValue
Config.Autoprovision.RETRY_TIMES.Times	Autop
Config.Autoprovision.REDIRECT.Url	URL-
Config.Autoprovision.REDIRECT.Enable	e: 0: 1:
Config.Autoprovision.REDIRECT.TransMac	Transport MAC 0: 1:
Config.Autoprovision.X.Name	autoprovision (X - 01 50)
Config.Autoprovision.X.Url	URL- autoprovision. : 1 ~ 127
Config.Autoprovision.X.User	1 63
Config.Autoprovision.X.Password	
Config.Autoprovision.X.ComAES	AES (16)
Config.Autoprovision.X.MacAES	AES (16) MAC
2.	
Config.Network.LAN.Type	LAN: 0: DHCP () 1: PPPoE 2: IP
Config.Network.LAN.StaticIP	IP
Config.Network.LAN.SubnetMask	
Config.Network.LAN.DefaultGateway	
Config.Network.LAN.PrimaryDNS	
Config.Network.LAN.SecondaryDNS	
Config.Network.PPPOE.User	PPPoE . 1 63
Config.Network.PPPOE.Pwd	
Config.Network.PC.Type	PC: 0: router 1: bridge
Config.Network.PC.RouterIP	IP, router
Config.Network.PC.SubnetMask	, router
Config.Network.PC.EnableDHCP	PC: 0: 1: ()
Config.Network.PC.StartIP	IP PC router
Config.Network.PC.EndIP	IP PC router
Config.Network.8021X.ModeOf8021X	8021x
Config.Network.8021X.Identity	8021x

Config.Network.8021X.PwdMd5	MD5 8021x
Config.Network.RTPPORT.Max	RTP
Config.Network.RTPPORT.Min	
Config.Network.QOS.SignalTos	QOS 0 63
Config.Network.QOS.RtpTos	rtptos QoS. 0 63
Config.Network.LLDP.LLDPEnable	LLDP. 0: (). 1:
Config.Network.LLDP.Interval	LLDP. 10 3600 .
Config.Network.VLAN.LanVlanEnable	VLAN LAN 0: () 1:
Config.Network.VLAN.LanVid	VLAN ID LAN 0 4094 (0)
Config.Network.VLAN.LanPriority	VLAN LAN 0 7 (0)
Config.Network.VLAN.PcVlanEnable	VLAN PC 0: () 1:
Config.Network.VLAN.PcVid	VLAN ID PC 0 4094 (0)
Config.Network.VLAN.PcPriority	VLAN LAN 0 7 (0)
Config.Network.SNMP.Enable	SNMP 0: () 1:
Config.Network.SNMP.Port	SNMP 0 65535
Config.Network.SNMP.TrustedIP	IP SNMP
Config.Network.VPN.Enable	VPN 0: () 1:
3. TR069	
Config.TR069.General.Enable	TR069: 0: () 1:
Config.TR069.General.Verison	TR069

Config.TR069.General.ResetFactory	TR069 ResetFactory 0: 1: ()
Config.TR069.DeviceInfo.ProvisioningCode	TR069
Config.TR069.DeviceInfo.DeviceName	DeviceInfo TR069
Config.TR069.DeviceInfo.Password	DeviceInfo TR069
Config.TR069.DeviceInfo.ErrorNumber	DeviceInfo TR069
Config.TR069.DeviceInfo.LongConnection	DeviceInfo TR069
Config.TR069.DeviceInfo.Description	DeviceInfo TR069
Config.TR069.DeviceInfo.LongConnectionAddr	DeviceInfo TR069
Config.TR069.ManagementServer.URL	URL ACS 1 63
Config.TR069.ManagementServer.Username	ACS 1 63
Config.TR069.ManagementServer.Password	
Config.TR069.ManagementServer.PeriodicInformEnable	ACS. 0: (). 1:
Config.TR069.ManagementServer.PeriodicInformInterval	ACS 3 3600 .
Config.TR069.ManagementServer.PeriodicInformTime	TR069
Config.TR069.ManagementServer.ParameterKey	TR069
Config.TR069.ManagementServer.ConnectionRequestURL	URL .
Config.TR069.ManagementServer.ConnectionRequestUsername	1 63
Config.TR069.ManagementServer.ConnectionRequestPassword	
Config.TR069.ManagementServer.STUNEnable	STUN 0: (). 1:
Config.TR069.ManagementServer.STUNServerAddress	STUN 1 63
Config.TR069.ManagementServer.STUNServerPort	STUN 1 65535
Config.TR069.ManagementServer.STUNUsername	STUN
Config.TR069.ManagementServer.STUNPassword	
Config.TR069.ManagementServer.STUNMaximumKeepAlivePeriod	STUN KeepAlive
Config.TR069.ManagementServer.STUNMinimumKeepAlivePeriod	
Config.TR069.ManagementServer.NATDetected	NAT STUN
Config.TR069.ManagementServer.UDPConnectionRequestAddress	UDP
Config.TR069.ManagementServer.UDPConnectionRequestAddressNotificationLimit	UDP
Config.TR069.ManagementServer.UpgradeManagement	
Config.TR069.Reboot.CmdKey	CMDKey

Config.TR069.Download.Enable	: 0: 1:
Config.TR069.Download.CmdKey	CMDKey
Config.TR069.Download.StartTime	
Config.TR069.Download.Ur	URL
Config.TR069.UserInfo.SubID	SubID
Config.TR069.UserInfo.AuthenticationType	
4.	
Config.AccountX. GENERAL.Enable	X (X 1 6) 0: () 1:
Config.AccountX. GENERAL.Label	() (1 6) 1 63
Config.AccountX. GENERAL.DisplayName	() (1 6) 1 63
Config.AccountX. GENERAL.Username	(1 6) 1 63
Config.AccountX. GENERAL.AuthName	(1 6)
Config.AccountX. GENERAL.Pwd	
Config.AccountX.GENERAL.UserAgent	UserAgent
Config.AccountX.GENERAL.ProxyRequire	ProxyRequire
Config.AccountX.SIP.Server	SIP (1 6) 1 63
Config.AccountX.SIP.Server2	SIP (1 6) 1 63
Config.AccountX.SIP.Port	SIP (1 6) 1 65535
Config.AccountX. SIP.Port2	SIP (1 6) 1 65535
Config.AccountX.SIP.ListenPort	(1 6) 1 65535
Config.AccountX.SIP.TransType	: 0: UDP () 1: TCP 2: TLS 3: DNS-SRV
Config.AccountX.SIP.ListenPortMin	
Config.AccountX.SIP.ListenPortMax	

Config.AccountX.OUTPROXY.Enable	outbound proxy server 0: () 1:
Config.AccountX.OUTPROXY.Server	ip / outbound proxy server 1 63
Config.AccountX.OUTPROXY.Port	ip / outbound proxy server- 1 65535
Config.AccountX.OUTPROXY.BakServer	ip / outbound proxy server 1 63
Config.AccountX.OUTPROXY.BakPort	ip / outbound proxy server- 1 65535
Config.AccountX.STUN.Enable	STUN 0: () 1:
Config.AccountX.STUN.Server	STUN . 1 63
Config.AccountX.STUN.Port	STUN 1 65535
Config.AccountX.ENCRYPTION.SRTPEncryption	SRTP 0: () 1:
Config.AccountX.ENCRYPTION.SRTPEncryptionAlg	SRTP
Config.AccountX.DTMF.Type	DTMF 0:Inband 1: RFC2833(Default) 2: Info 3: Info + Inband 4: Info + RFC2833
Config.AccountX.DTMF.Payload	RFC2833 payload, 96 127 (101)
Config.AccountX.DTMF.InfoType	DTMF «Info» 0:Disabled(default) 1:DTMF 2:DTMF-Relay 3:Telephone-Event
Config.AccountX.DTMF.Duration	DTMF
Config.AccountX.DTMF.Power	DTMF
Config.AccountX.NAT.NatTraversal	NAT Traversal
Config.AccountX.NAT.StunServer	NAT STUN 1 63
Config.AccountX.NAT.StunPor	NAT STUN 1 65535

Config.AccountX.NAT.UdpKeepEnable	NAT keep-alive 0: () 1:
Config.AccountX.NAT.UdpKeepInterval	NAT keep-alive 5 60 (30)
Config.AccountX.NAT.Rport	rport 1 65535
Config.AccountX.BLF.SubscribePeriod	BLF (1800). 1800 65535 (.) 1800
Config.AccountX.BLF.BlfListUri	URL BLF 1 63
Config.AccountX.BLF.BlfNotifyParseType	BLF Notify
Config.AccountX.BLF.BlfListCode	BLF
Config.AccountX.BLF.BlfListBargeInCode	BLF barge incode
Config.AccountX.VOICMSG.Number	1 63
Config.AccountX.MUSIC_SERVER.Enable	Music Server 0: () 1:
Config.AccountX.MUSIC_SERVER.Uri	URL Music Server 1 63
Config.AccountX.Anonymous_Call.Enable	« » 0: () 1:
Config.AccountX.Anonymous_Call.OnCode	« » 1 63
Config.AccountX.Anonymous_Call.OffCode	« »» 1 63
Config.AccountX.REJECT_ANONYMOUSCALL.Enable	« » 0: () 1:
Config.AccountX.REJECT_ANONYMOUSCALL.OnCode	/ . 1 63
Config.AccountX.REJECT_ANONYMOUSCALL.OffCode	
Config.AccountX.REG.Timeout	., 1800 65535 (1800)
Config.AccountX.REG.Timeout2	
Config.AccountX.CONFERENCE.Type	: 0: 1:

Config.AccountX.CONFERENCE.Uri	URL 1 63
Config.AccountX.AUTO_ANSWER.Enable	/ (1 6) 0: () 1:
Config.AccountX.SESSION.EnableTimer	/ : 0: () 1:
Config.AccountX.SESSION.Interval	(), 90 7200, - 1800
Config.AccountX.SESSION.Refreshers	., 1800 65535, 1800 - .
Config.AccountX.SUBSCRIBE.SubscribeRegister	/ : 0: () 1:
Config.AccountX.SUBSCRIBE.SubscribePeriod	(), 1800 65535, 1800
Config.AccountX.SUBSCRIBE.SubscribeACDExpire	ACD (), 1800 65535, 1800
Config.AccountX.SUBSCRIBE.SubscribeMWI	/ MWI 0: () 1:
Config.AccountX.SUBSCRIBE.SubscribeMWIExpire	MWI (), 1800 65535, 1800
Config.AccountX.CALL.Enable100Rel	/ 100 0: () 1:
Config.AccountX.CALL.CIDSource	CIDSource
Config.AccountX.CALL.Ptime	RTP, - 0 (), 10, 20, 30, 40, 50, 60
Config.AccountX.CALL.UserPhone	UserPhone. 0: 1:
Config.AccountX.CALL.RdrInfoDetection	
Config.AccountX.CALL.PreventSIPHacking	/ SIP 0: 1:
Config.AccountX.FEATURE_DND.Enable	/ DND 0: () 1:
Config.AccountX.FEATURE_DND.OnCode	/ DND 1 63
Config.AccountX.FEATURE_DND.OffCode	

Config.AccountX.FEATURE_DND.ReturnCode	DND 404(Not Found 480(Temporarily Unavailable) 486(Busy Here) 603(Decline)
Config.AccountX.FEATURE_FORWARD_ALWAYS.Enable	/ 0: () 1:
Config.AccountX.FEATURE_FORWARD_ALWAYS.Target	1 63
Config.AccountX.FEATURE_FORWARD_ALWAYS.OnCode	/ . 1 63
Config.AccountX.FEATURE_FORWARD_ALWAYS.Off Code	
Config.AccountX.FEATURE_FORWARD_BUSY.Enable	/ 0: () 1:
Config.AccountX.FEATURE_FORWARD_BUSY.Target	1 63
Config.AccountX.FEATURE_FORWARD_BUSY.OnCode	/ . 1 63
Config.AccountX.FEATURE_FORWARD_BUSY.OffCode	
Config.AccountX.FEATURE_FORWARD_TIMEOUT.Enable	/ 0: () 1:
Config.AccountX.FEATURE_FORWARD_TIMEOUT.Target	1 63
Config.AccountX.FEATURE_FORWARD_TIMEOUT.On Code	/ 1 63
Config.AccountX.FEATURE_FORWARD_TIMEOUT.Of fCode	
Config.AccountX.FEATURE_FORWARD_TIMEOUT.Ti meOut	. 0 120
Config.AccountX.AudioY.Enable	/ - Y (Y 0 12) (1 6)
Config.AccountX.AudioY.Name	
Config.AccountX.AudioY.Priority	
Config.AccountX.AudioY.Payload	
Config.AccountX.AOC.AocEnable	/ AOC 0: () 1:
Config.AccountX.RINGTONE.Type	(Ring1.wav)
Config.AccountX.ESCAPE_CHARACTER.Enable	ESCAPE. 0: 1:

Config.AccountX.ADVANCED.ShowMissedCall	: 0: 1:
Config.AccountX.HOTELING.Enable	/ HOTELING 0: 1:
Config.AccountX.HOTELING.User	HOTELING
Config.AccountX.HOTELING.Password	
Config.AccountX.HOTELING.AutoLogin	0: 1: 2:
5.	
Config.Forward.Always.Enable	0: () 1:
Config.Forward.Always.Target	1 63
Config.Forward.Always.OnCode	/ 1 63
Config.Forward.Always.OffCode	
Config.Forward.Busy.Enable	0: () 1:
Config.Forward.Busy.Target	1 63
Config.Forward.Busy.OnCode	/ 1 63
Config.Forward.Busy.OffCode	
Config.Forward.Timeout.Enable	/ 0: () 1:
Config.Forward.Timeout.Target	
Config.Forward.Timeout.Timeout	, 0 120
Config.Forward.Timeout.OnCode	/ 1 63
Config.Forward.Timeout.OffCode	
Config.Forward.CallPark.Enable	/ Call park 0: () 1:
Config.Forward.CallPark.Target	Call park 1 63

Config.Forward.CallPark.Line	, Call Park 0 (), 1, 2,3
Config.Forward.FORWARDMODE.Mode	
Config.Forward.FORWARDMODE.FeatureSync	
Config.Forward.ADVANCED.UseFwdAsTransfer	transfer
6. BroadSoft	
Config.BroadSoft.BroadSoftX.DisplayName	BroadSoft (0 5) 1 63
Config.BroadSoft.BroadSoftX.Server	URL BroadSoft (0 5) 1 255
Config.BroadSoft.BroadSoftX.Port	BroadSoft (0 5) 1 65535
Config.BroadSoft.BroadSoftX.User	BroadSoft (0 5)
Config.BroadSoft.BroadSoftX.Pwd	
7.	
Config.RemotePhoneBook.REMOTE_PHONE_BOOK X.DisplayName	, (0 4) 1 63
Config.RemotePhoneBook.REMOTE_PHONE_BOOK X.Url	URL (0 4) 1 255
Config.RemotePhoneBook.GENERAL.Search	/ . 0: 1:
Config.RemotePhoneBook.GENERAL.FlashInterval	Flash .
8. LDAP	
Config.Ldap.LDAP.NameFilter	1 63
Config.Ldap.LDAP.NumberFilter	
Config.Ldap.LDAP.Server	LDAP 1 63
Config.Ldap.LDAP.Port	LDAP 1 65535
Config.Ldap.LDAP.Root	LDAP 1 63
Config.Ldap.LDAP.User	LDAP
Config.Ldap.LDAP.Pwd	
Config.Ldap.LDAP.MaxHits	. 1 500 (50)
Config.Ldap.LDAP.NameAttr	1 63 .
Config.Ldap.LDAP.NumberAttr	
Config.Ldap.LDAP.DisplayName	
Config.Ldap.LDAP.Version	

onfig.Ldap.LDAP.SearchDelay	. 200 3000 (1000)
9. AreaCode	
Config.AreaCode.GENERAL.Code	dial plan- 1 63
Config.AreaCode.GENERAL.MaxLen	/ dial plan- 1 15
Config.AreaCode.GENERAL.MinLen	
Config.AreaCode.GENERAL.Account	dial plan- : 0 (), 1, 2, 3; 0 .
10. Feature ()	
Config.Features.CALL_WAITING.Enable	/ « » 0: 1: ()
Config.Features.CALL_WAITING.PlayTone	0: 1:
Config.Features.HOTLINE.Enable	/ Hotline 0: () 1:
Config.Features.HOTLINE.Number	Hotline 1 63
Config.Features.HOTLINE.Delay	Hotline () 0 5 .
Config.Features.AUTO_REDIAL.Enable	/ : 0: () 1:
Config.Features.AUTO_REDIAL.Interval	
Config.Features.AUTO_REDIAL.Times	
Config.Features.DND.Enable	/ DND 0: () 1:
Config.Features.DND.Status	DND
Config.Features.DND.ReturnCode	DND 404(Not Found 480(Temporarily Unavailable) 486(Busy Here) 603(Decline)
Config.Features.DND.OnCode	/ DND 1 63
Config.Features.DND.OffCode	

Config.Features.REJECT.ReturnCode	« » / 404(Not Found) 480(Temporarily Unavailable) 603(Decline).
Config.Features.INTERCOM.Enable	/ INTERCOM 0: 1: ()
Config.Features.INTERCOM.Mute	/ INTERCOM 0: () 1:
Config.Features.CALL_PICKUP.VisualAlert	Pickup
Config.Features.SpeedDial.LabelX	(01 12) 1 63
Config.Features.SpeedDial.NumberX	(01 12) 1 63
Config.Features.SpeedDial.LineX	(01 12) 0 (), 1, 2, 3
Config.Features.DIALNOW.Delay	0 5
Config.Features.Others.EarlyDTMF	/ EarlyDTMF
Config.Features.ACD.ACDAutoAvailable	/ ACD Auto Available 0: () 1:
Config.Features.ACD.ACDAutoAvailableTime	ACD Auto Available 0 180
Config.Features.ACD.ACDAutoLogin	ACD
Config.Features.ACTIONURL.SetupCompleted	URL -
Config.Features.ACTIONURL.Registered	
Config.Features.ACTIONURL.Unregistered	
Config.Features.ACTIONURL.RegisterFailed	
Config.Features.ACTIONURL.OffHook	
Config.Features.ACTIONURL.OnHook	
Config.Features.ACTIONURL.IncomingCall	
Config.Features.ACTIONURL.OutgoingCall	
Config.Features.ACTIONURL.Established	
Config.Features.ACTIONURL.Terminated	
Config.Features.ACTIONURL.OpenDND	
Config.Features.ACTIONURL.CloseDND	
Config.Features.ACTIONURL.OpenAlwaysForward	
Config.Features.ACTIONURL.CloseAlwaysForward	

Config.Features.ACTIONURL.OpenBusyForward	
Config.Features.ACTIONURL.CloseBusyForward	
Config.Features.ACTIONURL.OpenNoAnswerForward	
Config.Features.ACTIONURL.CloseNoAnswerForward	
Config.Features.ACTIONURL.TransferCall	
Config.Features.ACTIONURL.BlindTransfer	
Config.Features.ACTIONURL.AttendedTransfer	
Config.Features.ACTIONURL.Hold	
Config.Features.ACTIONURL.UnHold	
Config.Features.ACTIONURL.Mute	
Config.Features.ACTIONURL.UnMute	
Config.Features.ACTIONURL.MissedCall	
Config.Features.ACTIONURL.IPChanged	
Config.Features.ACTIONURL.ForwardInComingCall	
Config.Features.ACTIONURL.RejectInComingCall	
Config.Features.ACTIONURL.AnswerNewInCall	
Config.Features.ACTIONURL.TransferFinished	
Config.Features.ACTIONURL.TransferFailed	
Config.Features.ACTIONURL.IdleToBusy	
Config.Features.ACTIONURL.BusyToIdle	
Config.Features.ACTIONURL.Enable	
Config.Features.REMOTECONTROL.ActionURIAllowIPList	ip
Config.Features.SENDKEY.KeySendType	0: 1: #
11. Setting ()	

Config.Settings.LANGUAGE.Type	0: 1: 2: 3: 4: 5: 6: 7: 8: 9: 10: 11: 12: 13: 14:
Config.Settings.LANGUAGE.ActiveWebLang	/ web 0: 1:
Config.Settings.LANGUAGE.WebLang	: 0: 1: 2: 3: 4: 5: 6: 7: 8: 9: 10: 11: 12: 13: 14:
Config.Settings.DateTime.Type	DST type, : 0:Date 1:Week.
Config.Settings.DateTime.TimeFormat	0 (12), 1 (24)
Config.Settings.DATETIME.DateFormat	

Config.Settings.DateTime.Offset	() -300 300
Config.Settings.SNTP.Enable	/ NTP 0: 1: ()
Config.Settings.SNTP.TimeZone	.
Config.Settings.SNTP.Name	-11 +13 (0 -) (GMT -)
Config.Settings.SNTP.NTPServer1	NTP
Config.Settings.SNTP.NTPServer2	: NTP 1 - 0.pool.ntp.org NTP 2 - 1.pool.ntp.org
Config.Settings.SNTP.DTS	: 0: 1: 2:
Config.Settings.SNTP.Interval	() NTP (3600) 3600
Config.Settings.SNTP.StartTime	/ //
Config.Settings.SNTP.EndTime	
Config.Settings.Backlight.Level	. 0, 1, 2, 3, 4(), 5.
Config.Settings.Backlight.Time	. : 0 - , 1 - ., 10, 20 (), 30, 40, 50, 60, 90, 120
Config.Settings.BACKLIGHT.FreeLevel	
Config.Settings.General.DirectIP	/ IP: 0: 1: ()
Config.Settings.GENERAL.WebTitle	
Config.Settings.GENERAL.HttpUserAgent	HttpUserAgent
Config.Settings.LogLevel.Level	0, 1, 2, 3 (), 4, 5, 6, 7
Config.Settings.LOGLEVEL.RemoteSyslog	/ : 0: () 1:
Config.Settings.LOGLEVEL.RemoteServer	
Config.Settings.RingTone.Type	(Ring1.wav).
Config.Settings.RINGTONE.Lifetime	
Config.Settings.AUDIO.KeyVol	1 15 (8)

Config.Settings.AUDIO.KeyMidVol	
Config.Settings.AUDIO.RingVol	. 1 15 (8)
Config.Settings.AUDIO.RingMidVol	
Config.Settings.HANDFREE.SpKVol	« » 1 15 (8)
Config.Settings.HANDFREE.MicVol	« » 1 15 (8)
Config.Settings.HANDFREE.SpKMidValue	« »
Config.Settings.HANDFREE.MicMidValue	« »
Config.Settings.HANDFREE.SigToneVol	1 15 (8)
nfig.Settings.HANDFREE.SigToneMidVol	« »
Config.Settings.HandSet.SpKVol	1 15 (8)
Config.Settings.HandSet.MicVol	1 15 (8)
Config.Settings.HandSet.SpKMidValue	« »
Config.Settings.HandSet.MicMidValue	
Config.Settings.HandSet.SigToneVol	1 15 (8)
Config.Settings.HandSet.SigToneMidVol	
Config.Settings.HEADSET.Active	/ : 0: 1:
Config.Settings.HeadSet.SpKVol	1 15 (8)
Config.Settings.HeadSet.MicVol	1 15 (8)
Config.Settings.HEADSET.SpKMidValue	
Config.Settings.HEADSET.MicMidValue	
Config.Settings.HeadSet.SigToneVol	1 15 (8)
Config.Settings.HEADSET.SigToneMidVol	
Config.Settings.LOGIN.User	1 63 (admin -)
Config.Settings.LOGIN.Password	
Config.Settings.WEB_LOGIN.User	web
Config.Settings.WEB_LOGIN.Password	1 63 (admin -)

Config.Settings.WEB_LOGIN.Active	/
	0:
	1:
Config.Settings.WEB_LOGIN.SessionTimeOut	web
	60 14400 ()
Config.Settings.CallTimeOut.DialIn	
Config.Settings.CallTimeOut.DialOut	
Config.Settings.Ringer.KeywordX	(01 10)
Config.Settings.Ringer.RingtoneX	1 63
Config.Settings.HotDesking.ServerName	HotDesking
Config.Settings.HotDesking.ServerPort	HotDesking
Config.Settings.HotDesking.OutBoundName	HotDesking outbound
Config.Settings.HotDesking.OutBoundPort	HotDesking outbound
Config.Settings.HotDesking.PhoneName	HotDesking
Config.Settings.HotDesking.RegisterName	HotDesking
Config.Settings.HotDesking.PassWord	
Config.Settings.HotDesking.ServerName2	HotDesking
Config.Settings.HotDesking.ServerPort2	HotDesking
Config.Settings.DATEDISPLAY.DisplayMode	
Config.Settings.OTHERS.ProductMode	/ ProductMode
	0:
	1:
Config.Settings.OTHERS.Telnet	/ telnet
	0:
	1:
	telnet R&D, .
Config.Settings.OTHERS.QuickReset	/ :
	0:
	1:
Config.Settings.KEYPADLOCK.Type	
Config.Settings.KEYPADLOCK.Pin	
Config.Settings.KEYPADLOCK.Timeout	
Config.Settings.KEYPADLOCK.Emergency	
Config.Settings.SECURITY.OnlyAcceptTrusted	/ :
	0:
	1:
12. CallLog	
Config.Calllog.CALLLOGX.DisplayName	DisplayName («» 0 2)
Config.Calllog.CALLLOGX.Server	
Config.Calllog.CALLLOGX.Port	

Config.Callolog.CALLLOGX.User	
Config.Callolog.CALLLOGX.Pwd	
13. (Programmable Key)	
Config.Programable.LineKeyX.Type	(1 6) 1 19 1: DND 2: 3: MSG 4: 5: 6: Fwd 7: PickUp 8: Group PickUp 9: Intercom 10: Speed Dial 11: History 12: Favorite 13: 14: 15: ACD 16: BLF 17: BLFList 18: Call Return 19: HotDesking 20: Record 21: XML Browser 22:DTMF
Config.Programable.LineKeyX.Label	(1 6) 63
Config.Programable.LineKeyX.Param1	Param1 (1 6). Param1 (7-10, 16) 7 Param1= pick up 8, param1=group pick up target. 9, param1=intercom number. 10, param1=speed dial number. 16, param1=BLF number

Config.Programable.LineKeyX.Param2	param2 (1 6) 0:Auto 1:Account 1 2:Account 2 3:Account 3 4:Account 4 5:Account 5 6:Account 6
Config.Programable.LineKey.X.Param3	Param3 (1 6) 16, param3=Feature code 1 63
Config.Programable.SoftKeyX.Type	(01-04) 1: DND 2: Menu 3: MSG 4: Status 5: Book; 6: Fwd 7: PickUp 8: Group PickUp; 9: Intercom; 10: Speed Dial11 11: History 12: Favorite; 13: Redial; 18: Call Return 19:HotDesking 21:XML Browser
Config.Programable.SoftKeyX.Label	(1 4) 1 63
Config.Programable.SoftKeyX.Param1	param1 (1 6) param1 () 7, param1= pick up target. 8, param1=group pick up target. 9, param1 is the intercom number 10, param1=speed dial number.

Config.Programable.SoftKeyX.Param2	param2 (1 6) 0:Auto 1:Account 1 2:Account 2 3:Account 3 4:Account 4 5:Account 5 6:Account 6
Config.Programable.HOME.Type	HOME 0:N/A 1:DND 2:Menu 3:MSG 4:Status :Book 6:Fwd 7:PickUp 8:Group PickUp 9:Intercom 10:Speed Dial 11:History 12:Favorite 13:Redial 18: Call Return 19:HotDesking 21:XML Browser
Config.Programable.HOME.Param1	param1 (1 6) param1 () 7, param1= pick up target. 8, param1=group pick up target. 9, param1 is the intercom number 10, param1=speed dial number.

Config.Programable.HOME.Param2	param2 (1 6) 0:Auto 1:Account 1 2:Account 2 3:Account 3 4:Account 4 5:Account 5 6:Account 6
Config.Programable.OK.Type	OK 1:DND 2:Menu 3:MSG 4:Status :Book 6:Fwd 7:PickUp 8:Group PickUp 9:Intercom 10:Speed Dial 11:History 12:Favorite 13:Redial 18: Call Return 19:HotDesking 21:XML Browser
Config.Programable.OK.Param1	param1 (1 6) param1 () 7, param1= pick up target. 8, param1=group pick up target. 9, param1 is the intercom number 10, param1=speed dial number.

Config.Programable.OK.Param2	param2 (1 6) 0:Auto 1:Account 1 2:Account 2 3:Account 3 4:Account 4 5:Account 5 6:Account 6
Config.Programable.Cancel.Type	Cancel 0:N/A 1:DND 2:Menu 3:MSG 4:Status :Book 6:Fwd 7:PickUp 8:Group PickUp 9:Intercom 10:Speed Dial 11:History 12:Favorite 13:Redial 18: Call Return 19:HotDesking 21:XML Browser
Config.Programable.Cancel.Param1	param1 (1 6) param1 () 7, param1= pick up target. 8, param1=group pick up target. 9, param1 is the intercom number 10, param1=speed dial number.

Config.Programable.Cancel.Param2	param2 (1 6) 0:Auto 1:Account 1 2:Account 2 3:Account 3 4:Account 4 5:Account 5 6:Account 6
Config.Programable.FWD.Type	FWD 0:N/A 1:DND 2:Menu 3:MSG 4:Status :Book 6:Fwd 7:PickUp 8:Group PickUp 9:Intercom 10:Speed Dial 11:History 12:Favorite 13:Redial 18: Call Return 19:HotDesking 21:XML Browser
Config.Programable.FWD.Param1	param1 (1 6) param1 () 7, param1= pick up target. 8, param1=group pick up target. 9, param1 is the intercom number 10, param1=speed dial number.

Config.Programable.FWD.Param2	param2 (1 6) 0:Auto 1:Account 1 2:Account 2 3:Account 3 4:Account 4 5:Account 5 6:Account 6
Config.Programable.Book.Type	Book 0:N/A 1:DND 2:Menu 3:MSG 4:Status :Book 6:Fwd 7:PickUp 8:Group PickUp 9:Intercom 10:Speed Dial 11:History 12:Favorite 13:Redial 18: Call Return 19:HotDesking 21:XML Browser
Config.Programable.Book.Param1	param1 (1 6) param1 () 7, param1= pick up target. 8, param1=group pick up target. 9, param1 is the intercom number 10, param1=speed dial number.

Config.Programable.Book.Param2	param2 (1 6) 0:Auto 1:Account 1 2:Account 2 3:Account 3 4:Account 4 5:Account 5 6:Account 6
Config.Programable.Mute.Type	Mute 0:N/A 1:DND 2:Menu 3:MSG 4:Status :Book 6:Fwd 7:PickUp 8:Group PickUp 9:Intercom 10:Speed Dial 11:History 12:Favorite 13:Redial 18: Call Return 19:HotDesking 21:XML Browser
Config.Programable.Mute.Param1	param1 (1 6) param1 () 7, param1= pick up target. 8, param1=group pick up target. 9, param1 is the intercom number 10, param1=speed dial number.

Config.Programable.Mute.Param2	param2 (1 6) 0:Auto 1:Account 1 2:Account 2 3:Account 3 4:Account 4 5:Account 5 6:Account 6
Config.Programable.Redial.Type	Redial 0:N/A 1:DND 2:Menu 3:MSG 4:Status :Book 6:Fwd 7:PickUp 8:Group PickUp 9:Intercom 10:Speed Dial 11:History 12:Favorite 13:Redial 18: Call Return 19:HotDesking 21:XML Browser
Config.Programable.Redial.Param1	param1 (1 6) param1 () 7, param1= pick up target. 8, param1=group pick up target. 9, param1 is the intercom number 10, param1=speed dial number.

Config.Programable.Redial.Param2	param2 (1 6) 0:Auto 1:Account 1 2:Account 2 3:Account 3 4:Account 4 5:Account 5 6:Account 6
14. Voice	
Config.Voice.General.VAD	/ VAD () 0: 1:
Config.Voice.General.CNG	/ CNG () 0: 1:
Config.Voice.General.SideTone	sidetone (,). -32768 -3 (-327668)
Config.Voice.General.EchoCanceller	/ EchoCanceller: 0: 1: ()
Config.Voice.Jitter.Enable	/ - 0: 1: ()
Config.Voice.Jitter.Adaptive	-: 0: 1:
Config.Voice.Jitter.Min	(0)/ (300)/ (120) -
Config.Voice.Jitter.Max	
Config.Voice.Jitter.Nominal	
	0 1000 ()

Config.Voice.Tone.Country	: 0: 1: 2: 3: 4: 5: 6: T 7: 8: 9: 10: 11: 12: 13:
Config.Voice.DTMF.Repetition	DTMF
Config.Voice.DTMF.Duration	DTMF
Config.Voice.RTCP.Enable	/ RTCP 0: 1: ()
Config.Voice.RTCP.Interval	RTCP ()
Config.Voice.RTCP.RTCPXR	RTCPXR
Config.Voice.G726.Coding	/ G726 0: 1:
15. Tone	
Config.Tone.GENERAL.Busy	« »
Config.Tone.General.Ringback	ringback
Config.Tone.GENERAL.Congestion	
Config.Tone.GENERAL.Dialtone	dial tone.
Config.Tone.GENERAL.Disconnect	
Config.Tone.GENERAL.Callwait	« »
Config.Tone.GENERAL.Recorder	recorder
Config.Tone.GENERAL.SpecialDial	Special Dial
Config.Tone.GENERAL.SpecialInfo	Special Info
Config.Tone.GENERAL.StutterDial	Stutter Dial
Config.Tone.GENERAL.X	0 9
Config.Tone.GENERAL.Star	*
Config.Tone.GENERAL.Pound	#
16. XML Browser	

onfig.XMLBrowser.XMLBROWSER.VendorPrefix	XML VendorPrefix
Config.XMLBrowser.XMLBROWSER.MenuItemNode	XML ItemNode
Config.XMLBrowser.XMLBROWSER.DirectoryItemNode	XML ItemNode
Config.XMLBrowser.XMLBROWSER.MenuitemNameNode	XML ItemNode
Config.XMLBrowser.XMLBROWSER.MenuitemURLNode	URL XML ItemNode
Config.XMLBrowser.XMLBROWSER.DirectoryItemNameNode	XML
Config.XMLBrowser.XMLBROWSER.DirectoryItemTelephoneNode	XML ItemTelephoneNode
Config.XMLBrowser.XMLBROWSER.DirectoryItemPresenceNode	XML
17.	
Config.Firmware.Url	URL- ftp/tftp/http / https, .rom. 1 255 . 8
Config.Contact.Url	URL- ftp/tftp/http / https, .xml. 1 255 . 500
Config.Certificate.X.Ur	URL- ftp/tftp/http / https , .pem. 1 255